

## J Exercises

**Exercise III.1** Prove that projectors are idempotent, that is,  $P^2 = P$ .

**Exercise III.2** Prove that a normal matrix is Hermitian iff it has real eigenvalues.

**Exercise III.3** Prove that  $U(t) \stackrel{\text{def}}{=} \exp(-iHt/\hbar)$  is unitary.

**Exercise III.4** Use spectral decomposition to show that  $K = -i \log(U)$  is Hermitian for any unitary  $U$ , and thus  $U = \exp(iK)$  for some Hermitian  $K$ .

**Exercise III.5** Show that  $[L, M]$  and  $\{L, M\}$  are bilinear operators (linear in both of their arguments).

**Exercise III.6** Show that  $[L, M]$  is anticommutative, i.e.,  $[M, L] = -[L, M]$ , and that  $\{L, M\}$  is commutative.

**Exercise III.7** Show that  $LM = \frac{[L, M] + \{L, M\}}{2}$ .

**Exercise III.8** Prove that  $I, X, Y$ , and  $Z$  are unitary. (Use either the imaginary or real definition of  $Y$ .)

**Exercise III.9** Show that the  $X, Y, Z$  and  $H$  gates are Hermitian (their own inverses) and prove your answers. (Use either the imaginary or real definition of  $Y$ .)

**Exercise III.10** What is the effect of  $Y$  (imaginary definition) on the computational basis vectors?

**Exercise III.11** Prove the following useful identities:

$$HXH = Z, HYH = -Y, HZH = X.$$

**Exercise III.12** Show:

$$|0\rangle\langle 0| = \frac{1}{2}(I + Z), |0\rangle\langle 1| = \frac{1}{2}(X - Y), |1\rangle\langle 0| = \frac{1}{2}(X + Y), |1\rangle\langle 1| = \frac{1}{2}(I - Z),$$

where  $Y = \begin{pmatrix} 0 & -1 \\ 1 & 0 \end{pmatrix}$ .

**Exercise III.13** What is the matrix for CNOT in the standard basis? Prove your answer.

**Exercise III.14** What is the matrix for CCNOT in the standard basis? Prove your answer.

**Exercise III.15** Use Toffoli gates to implement NOT, OR and XOR.

**Exercise III.16** Use Toffoli gates to implement FAN-OUT. Does your implementation violate the No-cloning Theorem? Why or why not?

**Exercise III.17** Show that  $|+\rangle, |-\rangle$  is an ON basis.

**Exercise III.18** Prove:

$$\begin{aligned} |0\rangle &= \frac{1}{\sqrt{2}}(|+\rangle + |-\rangle), \\ |1\rangle &= \frac{1}{\sqrt{2}}(|+\rangle - |-\rangle). \end{aligned}$$

**Exercise III.19** Prove that  $Z|+\rangle = |-\rangle$  and  $Z|-\rangle = |+\rangle$ .

**Exercise III.20** Prove:

$$\begin{aligned} H(a|0\rangle + b|1\rangle) &= a|+\rangle + b|-\rangle, \\ H(a|+\rangle + b|-\rangle) &= a|0\rangle + b|1\rangle. \end{aligned}$$

**Exercise III.21** Prove  $H = (X + Z)/\sqrt{2}$ .

**Exercise III.22** Prove Eq. III.18 (p. 94).

**Exercise III.23** Show that three successive CNOTs, connected as in Fig. III.11 (p. 92), will swap two qubits.

**Exercise III.24** Recall the conditional selection between two operators (¶14, p. 93):  $|0\rangle\langle 0| \otimes U_0 + |1\rangle\langle 1| \otimes U_1$ . Suppose the control bit is a superposition  $|\chi\rangle = a|0\rangle + b|1\rangle$ . Show that:

$$(|0\rangle\langle 0| \otimes U_0 + |1\rangle\langle 1| \otimes U_1)|\chi, \psi\rangle = a|0, U_0\psi\rangle + b|1, U_1\psi\rangle.$$

**Exercise III.25** Show that the 1-bit full adder (Fig. III.15, p. 95) is correct.

**Exercise III.26** Show that the operator  $U_f$  is unitary:

$$U_f|x, y\rangle \stackrel{\text{def}}{=} |x, y \oplus f(x)\rangle,$$

**Exercise III.27** Verify the remaining superdense encoding transformations in ¶5 (p. 99).

**Exercise III.28** Verify the remaining superdense decoding transformations in ¶8 (p. 100).

**Exercise III.29** Complete the following step from the derivation of the Deutsch-Jozsa algorithm (Sec. D.1.b, ¶11, p. 112):

$$H|x\rangle = \sum_{z \in \mathbf{2}} \frac{1}{\sqrt{2}} (-1)^{xz} |z\rangle.$$

**Exercise III.30** Show that  $\text{CNOT}(H \otimes I) = (I \otimes H)C_Z H^{\otimes 2}$ , where  $C_Z$  is the controlled- $Z$  gate.

**Exercise III.31** Show that the Fourier transform matrix (¶10, p. 119, Sec. D.3.a) is unitary.

**Exercise III.32** Prove the claim in ¶20, p. 134 (Sec. D.4.b).

**Exercise III.33** Prove the claim in ¶23, p. 134 (Sec. D.4.b).

**Exercise III.34** Design a quantum gate array for the following syndrome extraction operator (¶3, p. 143, in Sec. D.5.d, p. 143):

$$S|x_1, x_2, x_3, 0, 0, 0\rangle \stackrel{\text{def}}{=} |x_1, x_2, x_3, x_1 \oplus x_2, x_1 \oplus x_3, x_2 \oplus x_3\rangle.$$

**Exercise III.35** Design a quantum gate array to apply the appropriate error correction for the extracted syndrome as given in ¶4, p. 143 (Sec. D.5.d, p. 143):

bit flipped	syndrome	error correction
none	$ 000\rangle$	$I \otimes I \otimes I$
1	$ 110\rangle$	$X \otimes I \otimes I$
2	$ 101\rangle$	$I \otimes X \otimes I$
3	$ 011\rangle$	$I \otimes I \otimes X$

**Exercise III.36** Prove that  $A_a A_a = \mathbf{1}$  (Sec. E.1.b).

**Exercise III.37** Prove that  $A_{ab,c} = \mathbf{1} + a^* a b^* b (c + c^* - \mathbf{1}) = \mathbf{1} + N_a N_b (A_c - \mathbf{1})$  is a correct definition of CCNOT by showing how it transforms the quantum register  $|a, b, c\rangle$  (Sec. E.1.b).

**Exercise III.38** Show that the following definition of Feynman's switch is unitary (Sec. E.1.b):

$$q^* c p + r^* c^* p + p^* c^* q + p^* c r.$$